

1 August 24, 2001

2 Express Mail Label No.: ET098671100US

PATENT

3

4

5

6

7

8

9

10

11

12

UNITED STATES PATENT APPLICATION

13

14

of

15

16

INVENTOR: CLARK H. GATES, II

17

A Citizen of the United States

18

550 North 250 East

19

PAROWAN, UTAH 84761

20

21

22

for

23

24

25

ELECTRICAL BOX WITH RECESSED FACEPLATE

BACKGROUND OF THE INVENTION

FIELD OF THE INVENTION

This invention relates to boxes for containing the wide variety of electrical equipment that is traditionally installed within electrical boxes, such as receptacles, modular telephone jacks, stationary connectors for coaxial cables, switches, and the like.

DESCRIPTION OF THE RELATED ART

Electrical equipment, such as receptacles, modular telephone jacks, stationary connectors for coaxial cables, switches, and the like is placed in the walls of almost all modern buildings. Into such devices, electrical connectors of various configurations can be removably inserted to provide a pathway for electricity to be supplied to such device to perform a variety of tasks, including powering an electrical appliance or carrying a signal for a telephone, computer, or television.

The standard faceplate for electrical instrumentalities, *i.e.*, receptacles, modular telephone jacks, stationary connectors for coaxial cables, switches, and the like, is basically a planar device which fits closely against the exterior surface of the wall and is attached, directly or indirectly, to a standard electrical box. An electrical box is the metallic or plastic box which contains one or more electrical receptacles (usually two or four), modular telephone jacks, stationary connectors for coaxial cables, switches, or the like, *i.e.*, electrical instrumentalities, that are permanently connected to the electrical wiring of the building.

Most electrical instrumentalities are connected with screws to the electrical box; the faceplate then is generally connected with screws or by snap-fitting to the electrical instrumentality and is thereby indirectly connected to the electrical box. Other electrical instrumentalities are attached to the faceplate, and the faceplate is directly connected with screws or by snap-fitting to the electrical box. In either case, one or more apertures, designated herein the instrumentality apertures, accommodate the portions of the electrical instrumentalities that are intended to be exposed.

Unlike a standard faceplate, a recessed faceplate, however, has only an edge which fits closely against the exterior surface of the wall; the portion of the recessed wall plate that is in the

1 same plane as the exterior surfaces of the electrical outlets is some distance inward from the
2 surface of the wall.

3 Recessed faceplates for receptacles, modular telephone jacks, stationary connectors for
4 coaxial cables, and the like, *i.e.*, electrical instrumentalities, provide the advantage that only the
5 electrical cords, telephone lines, or cables of an electrical appliance (if the electrical connector
6 that is physically associated with a particular electrical appliance is attached to a cord, line, or
7 cable, rather than being directly connected to the appliance) will extend outward from the plane
8 that forms the surface of a wall into which a receptacle, modular telephone jack, stationary
9 connector for coaxial cables, or the like, *i.e.*, an electrical instrumentality, has been mounted.
10 And in the case of switches, nothing will extend beyond the plane of the wall.

11 Two sections of the National Electrical Code are especially important for an electrical
12 box with a recessed faceplate.

13 Section 370-20 provides, "In walls or ceilings of concrete, tile, or other noncombustible
14 material, boxes shall be installed so that the front edge of the box will not be set back of the
15 finished surface more than ¼ in. (6.35 mm). In walls and ceilings constructed of wood or other
16 combustible material, boxes shall be flush with the finished surface or project therefrom."

17 And section 410-56 (e) states, in pertinent part, "Faceplates shall be installed so as to
18 completely cover the opening and seat against the mounting surface."

19 The present inventor is aware of a number of United States patents for electrical boxes
20 with a recessed faceplate, *viz.*, United States patent nos. 4,059,327; 4,936,794; 4,988,832;
21 5,257,946; 5,387,761; and 5,574,256. None of these, however, have the ability to accommodate
22 a recessed faceplate adapted to be extended so that, after installation of the box, the faceplate can
23 be adjusted so that the faceplate meets the preceding requirements of the National Electrical
24 Code; nor do they provide a mechanism for adapting a traditional electrical box to accommodate
25 a recessed faceplate.

26 United States patent no. 4,059,327 just has a fixed bracket **20** and **24** against which a
27 cover plate rigidly mounts in only one possible position. United States patent no. 4,936,794
28 simply has a recessed faceplate **26** rigidly attached to a tab **18** or **18a** in only one possible
29 position for a given embodiment of the box; and, in the embodiment using tab **18a**, a slot **36**
30 leaves an opening in the box, albeit on the outer side of the outlet. United States patent no.

4,988,832 employs a faceplate termed a bracket **12** rigidly attached to a stanchion **40, 42** in the box termed a housing **10** in only one possible position. United States patent no. 5,257,946 has a recessed cover plate **26** with a rear portion **48** that can be rigidly attached in only one possible position, with a screw, to the outlet, which is attached to the outlet box. United States patent no. 5,387,761 possesses a faceplate **36** that has a recess **42** that is only deep enough to accommodate a cover **54**; the faceplate **36** can be rigidly attached to the electrical box **14** in only one possible position. And in the device of United States patent no. 5,574,256, the outlet **20** is attached to a recessed wall **16** that is an integral portion of the box **10**; and the faceplate **30** mounts to the front of the box **10** in only one possible position.

Two of the preceding patents, *viz.*, nos. 4,988,832 and 5,387,761 include reclosable covers; no. 5,574,256 has a cover that is screwed in place; and United States patent no. 5,272,281 applies to an electrical outlet safety cover that is screwed in place. None of such covers, however, can be slid onto a faceplate.

Three patents, *i.e.*, United States patent no. 3,530,230; United States patent no. 4,090,769; and United States patent no. 4,918,259 are, though known for modifying electrical boxes that have already been installed.

United States patent no. 3,530,230 discloses two embodiments. The first has an outer frame member **12** and a cover plate **14**; the second, an outer frame **40** and a cover plate **46**. In both embodiments, however, there is a gap between the walls **18, 42** and the electrical box **30, 64**. The distance between the cover plate **14, 46** and the outer frame **12, 40** is only discretely (not continuously adjustable); the outer frame **12, 40** isn't fastened to anything; and, if the frame member **12** is flush against the wall, the cover plate **14** may not even touch the outlet because the distance between scoring of the tabs **20** may create a stop for the back of the cover plate **14** that is some distance in front of the outlet.

The device of United States patent no. 4,090,769 just plugs into an existing outlet, does not extend the electrical box, and has no indication that distance it extends from the existing electrical box is adjustable.

And United States patent no. 4,918,259 explicitly indicates that it does not extend the electrical box by stating, "The intent of the present invention is not to extend the receptacles, but rather to extend the cover" Moreover, the distance between the face of the cover frame **36**

1 and the outlet is only discretely (not continuously) adjustable; and the cover frame 36 does not
2 screw into place.

3 Finally, no electrical box is known to the Inventor wherein switches are mounted so that,
4 upon installation, the faces of the switches will be other than generally in the same plane as the
5 wall of the building in which the electrical box is located.

5

SUMMARY OF THE INVENTION

1 The present invention includes both a new electrical box with a recessed faceplate and an
2 electrical box with a recessed faceplate that is created by modifying a traditional electrical box.

3 Both have a one-piece faceplate; but the new electrical box is also designed to
4 accommodate a two-part faceplate which permits adjusting the distance between the outward
5 surface of the electrical instrumentality installed within the electrical box and the flange at the
6 front of the faceplate so that, after installation of the box, it can be assured that the flange of the
7 faceplate will be flush against the wall in which the electrical box has been installed and that a
8 wall of the faceplate will be flush against the outward surface of the installed electrical
9 equipment, thereby meeting, in a relatively easy fashion, the previously cited portions of the
10 National Electrical Code.

11 Furthermore, no screws or other components of a releasable fastener not employing
12 screws are exposed in any of the versions of the electrical box; and once the electrical
13 instrumentality is installed within the box, there are no openings in the electrical box.

14 The preceding is basically accomplished by enlarging both the height and width of the
15 mouth of the electrical box as well as adding threaded channels to the sides of the electrical box.

16 An extender is used with a traditional electrical box to create the ability to install
17 electrical instrumentalities within the assembled electrical box in a recessed aspect while still
18 insuring that the assembled box extends sufficiently close to the finished surface of the wall in
19 which the electrical box has been installed to meet the relevant portions of the National Electrical
20 Code.

21 Optionally, a sliding cover may be removably attached over either the one-piece or the
22 two-piece recessed faceplate.

23 An additional embodiment is a new electrical box for one or more switches wherein the
24 switches are to be oriented so that upon installation the faces of the switches will be other than
25 parallel to the wall of building in which the electrical box is placed.

BRIEF DESCRIPTION OF THE DRAWINGS

1 Figure 1 illustrates an Electrical Box with Recessed Faceplate having a one-piece box
2 recessed faceplate but designed to accommodate a two-piece recessed faceplate.

3 Figure 2 is the same embodiment as that of Figure 1 with the addition of a sliding cover.

4 Figure 3 depicts an Electrical Box with Recessed Faceplate having a two-piece recessed
5 faceplate.

6 Figure 4 is the same embodiment as that of Figure 3 with the addition of a sliding cover.

7 Figure 5 shows an Electrical Box with Recessed Faceplate that is created by modifying a
8 traditional electrical box.

9 Figure 6 portrays an Electrical Box with Recessed Faceplate for switches wherein the
10 switches are to be oriented so that upon installation the faces of the switches will be other than
11 parallel to the wall of building in which the electrical box is placed.

DESCRIPTION OF THE PREFERRED EMBODIMENT

1 The Electrical Box with Recessed Faceplate having a one-piece recessed faceplate but
2 designed to accommodate a two-piece recessed faceplate has, as illustrated in Figure 1, a box 1
3 into which a one-piece recessed faceplate 2 is removably inserted.

4 The box 1 has an open front or mouth 3 and a closed back 4, although the rear wall 4
5 contains the knock-out tabs that are well known in the art for creating openings through which
6 wiring can pass.

7 Attached to and projecting generally forward from the rear wall 4 is a lateral surface 1500
8 that connects the perimeter 1501 of the rear wall 4 to a first end 1502 of a connecting wall 1503
9 which connecting wall 1503 extends generally outward from, and preferably, perpendicular to,
10 the lateral surface 1500. Attached to and projecting generally forward from the second end 1504
11 and from the sides 1505 of the connecting wall 1503 is the first end 1506 of the front portion 11.
12 The second end 1507 of the front portion 11 forms the mouth 3 of the box 1.

13 The top 5, bottom 6, and sides 7 of the rear portion 8 of the box 1 each contain a channel
14 9 extending into the box 1 to accommodate a releasable fastener, preferably a screw, 10, with
15 each channel 9 extending toward the back 4 of the box 1 and preferably being generally centrally
16 located across the top 5, bottom 6, and each side 7 of the box 1.

17 In the preferred embodiment, the box 1 has a rectangular cross section. As illustrated in
18 Figure 1 and Figure 2, the front portion 11 of the box 1 extends beyond the top 5 and beyond the
19 bottom 6 of the rear portion 8. A top wall 12 that is preferably generally parallel to the front 3
20 and the back 4 of the box 1 runs from the top 5 of the rear portion 8 to the top 13 of the front
21 portion 11 of the box 1 and between the sides 7 of the box 1. Similarly, a bottom wall 16 that is
22 preferably generally parallel to the front 3 and the back 4 of the box 1 runs from the bottom 6 of
23 the rear portion 8 to the bottom 17 of the front portion 11 of the box 1 and between the sides 7 of
24 the box 1. Thus, in the preferred embodiment, the connecting wall 1503 is comprised of the top
25 wall 12 and the bottom wall 16 and sides 7 which are integrally formed with the sides 7 of the
26 rear portion 8 and the sides 7 of the front portion 11 of the box 1.

27 As suggested above, the interior ends 1001 of the channels 9 lie within the front portion
28 11 of the box 1; such ends 1001 are preferably covered except for a threaded aperture 1002 in
29 such ends 1001 and are preferably all substantially aligned with one another.

1 The channels **9** and, in the preferred embodiment, the threaded apertures **1002** of the
2 upper and lower channels **9** are used either to attach an electrical instrumentality **15** or a
3 faceplate to the box **1**. Whether the attachment is for an electrical instrumentality **15** or a
4 faceplate is determined by whether the electrical instrumentality **15** is intended to be attached to
5 the faceplate or directly to the box **1**. This is the same situation as for traditional electrical boxes.
6 If the electrical instrumentality **15** is intended to be attached directly to the box **1**, the threaded
7 apertures **1002** of the upper and lower channels **9** each accommodate a screw **10** for holding the
8 electrical instrumentality **15** to the box **1**, as illustrated in Figure 1 through Figure 4. Otherwise,
9 the threaded apertures **1002** of the upper and lower channels **9** would be available to retain a
10 screw **10** for holding the faceplate to the box **1**.

11 Furthermore, as is the case with traditional faceplates, attachment of an electrical
12 instrumentality **15** to a faceplate can be permanent or releasable, at least when the faceplate is
13 intended to be attached directly to the box **1**.

14 Retention of faceplates, whether one-piece or two-piece, to electrical boxes **1** is, as
15 indicated above, preferably done with screws **10**, as illustrated in Figure 1 through Figure 4,
16 since screws tend to pull the faceplate against the mounting surface. However, the only essential
17 feature is that a releasable fastener be used to hold the faceplate either directly to the box **1** or
18 indirectly to the box **1** by having the faceplate directly attached, with a releasable fastener, to an
19 electrical instrumentality **15** that is, itself, directly connected to the box **1** with a releasable
20 fastener. Thus, for example, any type of snap-fit for a faceplate to the box **1** or to the electrical
21 instrumentality **15** that is well known in the art may be employed.

22 For the embodiments depicted in Figure 1 through Figure 4, the top wall **12** contains an
23 aperture **19** to accommodate a screw **10** that extends through the top wall **12** outside the box **1**.
24 Similarly, the bottom wall **16** contains an aperture **20** to accommodate a screw **10** that extends
25 through the bottom wall **16** outside the box **1** for the same purpose as the aperture **19**. Apertures
26 **19**, **20** accommodate screws **10** which are used to attach faceplates to the type of electrical
27 instrumentality **15** depicted in Figure 1 through Figure 4, using threaded aperture **101** of the
28 electrical instrumentality **15**. For different electrical instrumentalities, however, the number and
29 location of apertures for attaching a faceplate to an electrical instrumentality **15** depend upon
30 particular electrical instrumentality **15** that is utilized.

The channels **9** on the sides **7** of the box **1** and their associated threaded apertures **1002** accommodate screws **10** to draw toward the box **1** and retain the outer portion **24** of a two-piece recessed faceplate **25**, as shown in Figure 3.

The one-piece recessed faceplate **2** has a rear wall **26** containing one or more instrumentality apertures **27** to accommodate the electrical instrumentality **15**. Attached to and projecting generally forward from the rear wall **26** is an interior surface **1400** that connects the perimeter **1401** of the rear wall **26** to a flange **33**. The rear wall **26** has substantially the same shape as does the cross section of the front portion **11** of the box **1**. In the case of a box **1** having a traditionally rectangular cross section, as depicted in Figure 1 and Figure 2, the interior surface **1400** comprises a top **27**, bottom **28**, and two sides **29** attached to one another so as to form a four-sided object. To the front **30** of the top **27**, the front **31** of the bottom **28**, and the front **32** of the two sides **29** is attached a flange **33**, the back side **34** of which flange **33** is designed to seat against the mounting surface. The faceplate **2** has, in comparison to the box **1**, dimensions such that the flange **33** extends from the interior surface **1400** of the box **1** to a position laterally beyond the front of the mouth **3**.

The rear wall **26** is also adapted to accommodate a releasable fastener for fastening the faceplate **2** directly or indirectly, through the electrical instrumentality **15**, to the box **1**. Preferably, this consists of one or more apertures **1003** to accommodate screws **10**.

Thus, the Electrical Box with Recessed Faceplate having a one-piece recessed faceplate has a box **1** adapted to accommodate a two-piece recessed faceplate **25**, has no screws **10** or analogous components of another type of releasable fastener exposed within the box **1** behind the installed electrical equipment **15**, and possesses no substantial gaps or apertures other than those designed to accommodate the installed electrical equipment **15** and screws **10** or components of another type of releasable fastener. The description to this point has concentrated upon the embodiments depicted in Figure 1 through Figure 4. Any embodiment utilizing the inventive features described in the first sentence of this paragraph would, however, fall within the scope of this invention, *e.g.*, the cross section of the box **1** need not necessarily be rectangular.

Attached to the top 13 of the front portion 11 or to the top 5 of the rear portion 8 of the box 1, but preferably to the top 13 of the front portion 11 of the box 1, and also to the bottom 17 of the front portion 11 or to the bottom 6 of the rear portion 8 of the box 1, but preferably to the

1 bottom 17 of the front portion 11 of the box 1, are projections 134 between which nails can be
2 inserted to fasten the box 1 to a surface, preferably a stud.

3 As shown in Figure 2, the sides 35 of the flange 33 optionally contain channels 36
4 running along the edge 37 of the flange 33 to accommodate longitudinal tabs 38 of a cover 39 so
5 that the cover 39 can be removably placed over the Electrical Box with Recessed Faceplate. In
6 the embodiment of Figure 2, the lower portion 40 of the flange 33 contains one or more
7 indentations 41 to accommodate the electrical cords, telephone lines, or cables of any electrical
8 instrumentality that may be plugged into the receptacle 15.

9 The cover 39 preferably has a front surface 141, a top 42 connected to the front surface
10 41, and two sides 43 each of which is connected to the front surface 141 and to the top 42 to
11 form a four-sided structure. The longitudinal tabs 38 extend inward from each side 43, and the
12 top 42 functions as a stop to preclude the cover 39 from sliding below the flange 33.

13 The outer portion 24 of the two-piece recessed faceplate 25 is constructed just as is the
14 one-piece recessed faceplate 2 except that such outer portion 24 does not have a rear wall 26 but
15 instead has attached to each side 29 a longitudinal projection 201 extending inward having an
16 aperture 44 to accommodate a screw 10 or other releasable fastener that will draw toward the box
17 1, and retain, the outer portion 24 of the two-piece recessed faceplate 25. This pulls the back
18 side 34 of the flange 33 against the mounting surface.

19 The inner portion 45 of the two-piece recessed faceplate 25 is constructed the same as the
20 one-piece recessed faceplate 2 except that it does not have the flange 33 but does possess the
21 number of apertures 46, two apertures 46 in the case of screws 10, to accommodate the
22 releasable fasteners that draw the outer portion 24 of the two-piece recessed faceplate 25 to the
23 box 1.

24 The top 27, bottom 28, and two sides 29 for the outer portion 24 of the two-piece
25 recessed faceplate 25 are sized so that they will slide along the inside of the top 27, bottom 28,
26 and two sides 29, respectively, of the inner portion 45 in order that there will substantially be no
27 gaps between these corresponding features.

28 As depicted in Figure 4, the outer portion 45 of the two-piece recessed faceplate 25
29 optionally is designed, just as is the one-piece recessed faceplate 2, to have a cover 39.

1 The one-piece recessed faceplate 2 is also utilized with the embodiment of Figure 5,
2 which employs a traditional electrical box 46.

3 An extender 47 is placed around the traditional electrical box 46 to create an electrical
4 box that is designed to have the electrical instrumentality 15 located in essentially the same
5 position as with the unmodified traditional electrical box 46 but having the electrical box extend
6 beyond that position.

7 The extender 47 has a first side 48 and a second side 49 constructed to slide along the
8 outside surface of the sides 7 of the traditional electrical box 46, preferably leaving no substantial
9 gaps between the sides 7 of the traditional electrical box 46 and the sides 48, 49 of the extender
10 47. Because the traditional electrical box 46 has two projections 50 on the side 7 along which
11 the second side 49 of the extender 47 slides, the second side 49 of the extender 47 contains two
12 channels 51 to accommodate the projections 50.

13 At a distance, from the back 52 of the sides 48, 49 of the extender 47, greater than the
14 distance between the open front 3 of the traditional electrical box 46 and the projections 134 to
15 hold nails 401, and preferably a distance substantially equal to the distance between the open
16 front 3 and the closed back 4 of the traditional electrical box 46, a wall 53 is attached to the sides
17 48, 49 and runs from the bottom 54 to the top 55 of the sides 48, 49 of the extender 47 and from
18 the first side 48 to the second side 49 of the extender 47. The sides 48, 49 and the wall 53 of the
19 extender proceed both above and below the traditional electrical box 46. Each side 48, 49
20 contains an aperture 301 that will be above a height equal to the top 5 and an aperture 302 that
21 will be below the level of the bottom 6 of a traditional electrical box 46, with such apertures 301,
22 302 also being at a position that will be in general alignment with the projections 134 when the
23 extender 47 is placed on a traditional electrical box 46. The apertures 301, 302 then
24 accommodate the nails 401 that go through the projections 134.

25 Contained within the wall 53 are one or more instrumentality apertures 154 to
26 accommodate the electrical instrumentality 15. The one or more instrumentality apertures 154
27 can extend as far as desired toward the sides 48, 49, even reaching the sides 48, 49.

28 The wall 53 also has a lower aperture 55 and an upper aperture 56, placed so as to be
29 generally aligned with the lower channel 9 and upper channel 9 of a traditional electrical box 46
30 when the extender 47 has been placed on a traditional electrical box 46, for screws 10 that will

1 bottom 606 of the back panel 602, a front panel 607 attached to a second end 608 of each
2 L-shaped side 601 running between the L-shaped sides from the bottom 605 of the L-shaped
3 sides to the vertex 609 of the L and also attached to the bottom panel 604, and a U-shaped ledge
4 610 having the inside 611 of the bottom 612 of the U-shaped ledge 610 attached to the top 613 of
5 the front panel 607 and the outside 614 of the legs 615 of the U-shaped ledge 610 attached to the
6 generally L-shaped sides 601 in substantial alignment with the inside edge 616 of the shorter leg
7 617 of the L.

8 Thus, an aperture 618 exists in the U-shaped ledge 610 to accommodate a switch 619. A
9 threaded aperture 620 in each leg 615 of the U-shaped ledge 610 accommodates a screw 10 to
10 hold the switch 619 in place.

11 A primary aperture 621, consequently, also exists above the front panel 607. An insert
12 622 having a top 623, bottom 624, and two sides 625 has an aperture 626 in the bottom to
13 accommodate the switch 619. The insert 622 slidably mounts within the primary aperture 621,
14 *i.e.*, above the U-shaped ledge 610. An aperture 627 in one or more ends 628 of the bottom 624
15 of the insert 622 is designed to be substantially aligned with one or more secondary threaded
16 apertures 629 in the legs 615 of the U-shaped ledge 610 after the insert 622 has been placed into
17 the primary aperture 621 in order to accommodate a screw 10 to hold the insert 622 in place.

18 Finally, a flange 630 extends from the outer edges 631 of the insert 622 generally
19 perpendicular to the top 623, bottom 624, and two sides 625 of the insert 622. The flange 630 is
20 designed to seat substantially against the mounting surface.

21 Whenever in the preceding discussion a threaded aperture has been mentioned, a
22 non-threaded aperture could, instead, be used together with a threaded nut; and the term
23 "threaded aperture" is intended to encompass such structure.

24